

Internet Engineering Task Force (IETF)
Request for Comments: 5907
Category: Standards Track
ISSN: 2070-1721

H. Gerstung
Meinberg
C. Elliott

B. Haberman, Ed.
JHU APL
June 2010

Definitions of Managed Objects for
Network Time Protocol Version 4 (NTPv4)

Abstract

The Network Time Protocol (NTP) is used in networks of all types and sizes for time synchronization of servers, workstations, and other networked equipment. As time synchronization is more and more a mission-critical service, standardized means for monitoring and management of this subsystem of a networked host are required to allow operators of such a service to set up a monitoring system that is platform- and vendor-independent. This document provides a standardized collection of data objects for monitoring the NTP entity of such a network participant and it is part of the NTP version 4 standardization effort.

5Status of This Memo

This is an Internet Standards Track document.

This document is a product of the Internet Engineering Task Force (IETF). It represents the consensus of the IETF community. It has received public review and has been approved for publication by the Internet Engineering Steering Group (IESG). Further information on Internet Standards is available in Section 2 of RFC 5741.

Information about the current status of this document, any errata, and how to provide feedback on it may be obtained at <http://www.rfc-editor.org/info/rfc5907>.

Copyright Notice

Copyright (c) 2010 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to BCP 78 and the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must include Simplified BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

Table of Contents

1. Introduction	2
2. Conventions Used in This Document	3
3. The Internet-Standard Management Framework	3
4. Technical Description	3
5. MIB Definition	4
6. IANA Considerations	23
7. Security Considerations	23
8. Acknowledgments	24
9. References	24
9.1. Normative References	24
9.2. Informative References	2

1. Introduction

The NTPv4 MIB module is designed to allow Simple Network Management Protocol (SNMP) to be used to monitor and manage local NTP [RFC5905] entities. It provides a collection of data objects that can be queried using the SNMP protocol and represent the current status of the NTP entity. This includes general information about the NTP entity itself (vendor, product, version) as well as connectivity to upstream NTP servers used as sources of reference time and to hardware reference clocks like radio clocks. The most important values are included in order to be able to detect failures before they can have an impact on the overall time synchronization status of the network. There are also a collection of notification objects to inform about state changes in the NTP entity. There are objects to control these notifications as well.

2. Conventions Used in This Document

The capitalized key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [RFC2119].

3. The Internet-Standard Management Framework

For a detailed overview of the documents that describe the current Internet-Standard Management Framework, please refer to section 7 of RFC 3410 [RFC3410].

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. MIB objects are generally accessed through the Simple Network Management Protocol (SNMP). Objects in the MIB are defined using the mechanisms defined in the Structure of Management Information (SMI). This memo specifies a MIB module that is compliant to the SMIV2, which is described in STD 58, RFC 2578 [RFC2578], STD 58, RFC 2579 [RFC2579] and STD 58, RFC 2580 [RFC2580].

4. Technical Description

The NTPv4 MIB module is divided into sections for general server information, current NTP entity status, status information of all mobilized associations (e.g., unicast upstream time servers, multicast or broadcast, time references, and hardware clocks), NTP entity control objects, NTP objects used only for notifications, as well as SNMP notification definitions for core events.

The general server information section contains static information and can be queried to identify which NTP implementation is running on a host. This includes the vendor and product name of the running NTP software as well as version information, hardware/os platform identity, and the time resolution of the underlying OS.

Section 2 (current NTP status) includes data objects that represent the current operational status of the NTP entity.

The third section contains data objects that represent the set of time references ("associations") with which the NTP entity is currently working.

The fourth section contains objects that can be used to control the NTP entity. The currently defined objects control how often the heartbeat interval notification is sent out and which notifications are enabled.

The fifth section contains objects that are only used as varbinds in notifications. There is currently only one object in this section -- a message that adds a cleartext event message to notifications.

Certain important events can occur while the NTP entity is running. The notification section defines SNMP notifications for a collection of the most important ones ("core events") and additionally provides a heartbeat notification as well as a test notification to allow management systems to test the reception of NTP-related notifications as well as enable heartbeat-based monitoring systems to assure that the NTP entity is still up and running.

Some values are included both in numeric and in human-readable (string) format. This has been done to simplify the representation of a status information. If the two representations of a certain value differ, the numeric representation takes precedence.

5. MIB Definition

```
-- *****
--
--   The Network Time Protocol Version 4
--   Management Information Base (MIB)
--
--   Authors: Heiko Gerstung (heiko.gerstung@meinberg.de)
--            Chris Elliott (chelliot@pobox.com)
--
--   for the Internet Engineering Task Force (IETF)
--   NTP Working Group (ntpwg)
--
-- *****
--   Rev 1.00
--   Published as RFC 5907
--
-- *****
```

NTPv4-MIB DEFINITIONS ::= BEGIN

IMPORTS

```
MODULE-IDENTITY, OBJECT-TYPE , mib-2, Integer32, NOTIFICATION-TYPE,
Unsigned32, Counter32, TimeTicks
FROM SNMPv2-SMI -- RFC 2578
MODULE-COMPLIANCE, OBJECT-GROUP, NOTIFICATION-GROUP
FROM SNMPv2-CONF -- RFC 2580
DisplayString, TEXTUAL-CONVENTION
FROM SNMPv2-TC -- RFC 2579
```

InetAddressType, InetAddress
FROM INET-ADDRESS-MIB -- RFC 4001
Utf8String
FROM SYSAPPL-MIB; -- RFC 2287

ntpSnmpMIB MODULE-IDENTITY

LAST-UPDATED "201005170000Z" -- May 17, 2010
ORGANIZATION "The IETF NTP Working Group (ntpwg)"
CONTACT-INFO
" WG Email: ntpwg@lists.ntp.isc.org
Subscribe:
<https://lists.ntp.isc.org/mailman/listinfo/ntpwg>

Heiko Gerstung
Meinberg Funkhuren Gmbh & Co. KG
Lange Wand 9
Bad Pyrmont 31812
Germany

Phone: +49 5281 9309 25
Email: heiko.gerstung@meinberg.de

Chris Elliott
1516 Kent St.
Durham, NC 27707
USA

Phone: +1-919-308-1216
Email: chelliot@pobox.com

Brian Haberman
11100 Johns Hopkins Road
Laurel, MD 20723
USA

Phone: +1-443-778-1319
Email: brian@innovationslab.net"

DESCRIPTION

"The Management Information Base for NTP time entities.

Copyright (c) 2010 IETF Trust and the persons identified as
authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or
without modification, is permitted pursuant to, and subject
to the license terms contained in, the Simplified BSD License
set forth in Section 4.c of the IETF Trust's Legal Provisions
Relating to IETF Documents

```
(http://trustee.ietf.org/license-info)."  
  
REVISION      "201005170000Z"  
DESCRIPTION  
    "This revision of the MIB module is published as RFC 5907."  
  
 ::= { mib-2 197 }  
  
ntpSnmpMIBObjects OBJECT IDENTIFIER ::= { ntpSnmpMIB 1 }  
  
-- MIB contains 6 groups  
  
ntpEntInfo      OBJECT IDENTIFIER ::= { ntpSnmpMIBObjects 1 }  
ntpEntStatus    OBJECT IDENTIFIER ::= { ntpSnmpMIBObjects 2 }  
ntpAssociation  OBJECT IDENTIFIER ::= { ntpSnmpMIBObjects 3 }  
ntpEntControl   OBJECT IDENTIFIER ::= { ntpSnmpMIBObjects 4 }  
ntpEntNotifObjects OBJECT IDENTIFIER ::= { ntpSnmpMIBObjects 5 }  
  
--  
-- Textual Conventions  
--  
  
NtpStratum ::= TEXTUAL-CONVENTION  
    DISPLAY-HINT "d"  
    STATUS      current  
    DESCRIPTION  
        "The NTP stratum, with 16 representing no stratum."  
    SYNTAX      Unsigned32 (1..16)  
  
NtpDateTime ::= TEXTUAL-CONVENTION  
    DISPLAY-HINT "4d:4d:4d.4d"  
    STATUS      current  
    DESCRIPTION  
        "NTP date/time on the device, in 128-bit  
        NTP date format.  If time is not synchronized, this  
        field shall be a zero-length string.  
  
        This trusted certificate (TC) is not to be used for objects  
        that are used to set the time of the node querying this  
        object.  NTP should be used for this -- or at least SNTP."  
    REFERENCE   "RFC 5905, section 6"  
    SYNTAX      OCTET STRING (SIZE (0 | 16))  
  
--  
-- Section 1: General NTP Entity information objects  
--          (relatively static information)  
--
```

ntpEntSoftwareName OBJECT-TYPE

SYNTAX Utf8String

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The product name of the running NTP version, e.g., 'ntpd'."

::= { ntpEntInfo 1 }

ntpEntSoftwareVersion OBJECT-TYPE

SYNTAX Utf8String

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The software version of the installed NTP implementation
as a full version string, e.g., 'ntpd-4.2.0b@1.1433 ...'"

::= { ntpEntInfo 2 }

ntpEntSoftwareVendor OBJECT-TYPE

SYNTAX Utf8String

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The vendor/author of the installed NTP version."

::= { ntpEntInfo 3 }

ntpEntSystemType OBJECT-TYPE

SYNTAX Utf8String

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"General hardware/os platform information,
e.g., 'Linux 2.6.12 / x86'."

-- freely configurable, default is OS Version / Hardware platform

::= { ntpEntInfo 4 }

ntpEntTimeResolution OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The time resolution in integer format, where the resolution
is represented as divisions of a second, e.g., a value of 1000
translates to 1.0 ms."

::= { ntpEntInfo 5 }

ntpEntTimePrecision OBJECT-TYPE

SYNTAX Integer32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The entity's precision in integer format, shows the precision.

A value of -5 would mean $2^{-5} = 31.25$ ms."

::= { ntpEntInfo 6 }

ntpEntTimeDistance OBJECT-TYPE

SYNTAX DisplayString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The distance from this NTP entity to the root time reference (stratum 0) source including the unit, e.g., '13.243 ms'."

::= { ntpEntInfo 7 }

--

-- Section 2: Current NTP status (dynamic information)

--

ntpEntStatusCurrentMode OBJECT-TYPE

SYNTAX INTEGER {

notRunning(1),
notSynchronized(2),
noneConfigured(3),
syncToLocal(4),
syncToRefclock(5),
syncToRemoteServer(6),
unknown(99)

}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The current mode of the NTP. The definition of each possible value is:

notRunning(1) - NTP is not running.

notSynchronized(2) - NTP is not synchronized to any time source (stratum = 16).

noneConfigured(3) - NTP is not synchronized and does not have a reference configured (stratum = 16).

syncToLocal(4) - NTP is distributing time based on its local clock (degraded accuracy and/or reliability).

syncToRefclock(5) - NTP is synchronized to a local hardware refclock (e.g., GPS).


```
        syncToRemoteServer(6) - NTP is synchronized to a remote
                                NTP server ('upstream' server).
        unknown(99) - The state of NTP is unknown."
 ::= { ntpEntStatus 1 }
```

ntpEntStatusStratum OBJECT-TYPE

```
SYNTAX      NtpStratum
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "The NTP entity's own stratum value. Should be a stratum of
     syspeer + 1 (or 16 if no syspeer)."
```

```
 ::= { ntpEntStatus 2 }
```

ntpEntStatusActiveRefSourceId OBJECT-TYPE

```
SYNTAX      Unsigned32 ( 0..99999 )
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "The association ID of the current syspeer."
```

```
 ::= { ntpEntStatus 3 }
```

ntpEntStatusActiveRefSourceName OBJECT-TYPE

```
SYNTAX      Utf8String
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "The hostname/descriptive name of the current reference source
     selected as syspeer, e.g., 'ntp1.ptb.de' or 'GPS' or
     'DCFi', ..."
```

```
 ::= { ntpEntStatus 4 }
```

ntpEntStatusActiveOffset OBJECT-TYPE

```
SYNTAX      DisplayString
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "The time offset to the current selected reference time source
     as a string including unit, e.g., '0.032 ms' or '1.232 s'."
```

```
 ::= { ntpEntStatus 5 }
```

ntpEntStatusNumberOfRefSources OBJECT-TYPE

```
SYNTAX      Unsigned32 (0..99)
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "The number of reference sources configured for NTP."
```

```
 ::= { ntpEntStatus 6 }
```

ntpEntStatusDispersion OBJECT-TYPE

SYNTAX DisplayString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The root dispersion of the running NTP entity, e.g., '6.927'."

::= { ntpEntStatus 7 }

ntpEntStatusEntityUptime OBJECT-TYPE

SYNTAX TimeTicks

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The uptime of the NTP entity, (i.e., the time since ntpd was (re-)initialized not sysUptime!). The time is represented in hundreds of seconds since Jan 1, 1970 (00:00:00.000) UTC."

::= { ntpEntStatus 8 }

ntpEntStatusDateTime OBJECT-TYPE

SYNTAX NtpDateTime

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The current NTP date/time on the device, in 128-bit NTP date format. If time is not synchronized, this field shall be a zero-length string."

This object can be used to timestamp events on this node and allow a management station to correlate different time objects. For example, a management station could query this object and sysUptime in the same operation to be able to relate sysUptime to NTP time.

This object is not to be used to set the time of the node querying this object. NTP should be used for this -- or at least SNTP."

REFERENCE "RFC 5905, section 6"

::= { ntpEntStatus 9 }

ntpEntStatusLeapSecond OBJECT-TYPE

SYNTAX NtpDateTime

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"Date the next known leap second will occur. If there is no leap second announced, then this object should be 0."

::= { ntpEntStatus 10 }

ntpEntStatusLeapSecDirection OBJECT-TYPE

SYNTAX Integer32 (-1..1)
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"Direction of next known leap second. If there is no
leap second announced, then this object should be 0."
::= { ntpEntStatus 11 }

ntpEntStatusInPkts OBJECT-TYPE

SYNTAX Counter32
UNITS "packets"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"The total number of NTP messages delivered to the
NTP entity from the transport service.
Discountinuties in the value of this counter can occur
upon cold start or reinitialization of the NTP entity, the
management system and at other times as indicated by
discontinuties in the value of sysUpTime."

::= { ntpEntStatus 12 }

ntpEntStatusOutPkts OBJECT-TYPE

SYNTAX Counter32
UNITS "packets"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"The total number of NTP messages delivered to the
transport service by this NTP entity.
Discountinuties in the value of this counter can occur
upon cold start or reinitialization of the NTP entity, the
management system and at other times as indicated by
discontinuties in the value of sysUpTime."

::= { ntpEntStatus 13 }

ntpEntStatusBadVersion OBJECT-TYPE

SYNTAX Counter32
UNITS "packets"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"The total number of NTP messages that were delivered
to this NTP entity and were for an unsupported NTP
version."

Discontinuities in the value of this counter can occur upon cold start or reinitialization of the NTP entity, the management system and at other times as indicated by discontinuities in the value of sysUpTime."

::= { ntpEntStatus 14 }

ntpEntStatusProtocolError OBJECT-TYPE

SYNTAX Counter32

UNITS "packets"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The total number of NTP messages that were delivered to this NTP entity and this entity was not able to process due to an NTP protocol error.

Discontinuities in the value of this counter can occur upon cold start or reinitialization of the NTP entity, the management system and at other times as indicated by discontinuities in the value of sysUpTime."

::= { ntpEntStatus 15 }

ntpEntStatusNotifications OBJECT-TYPE

SYNTAX Counter32

UNITS "notifications"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The total number of SNMP notifications that this NTP entity has generated.

Discontinuities in the value of this counter can occur upon cold start or reinitialization of the NTP entity, the management system and at other times as indicated by discontinuities in the value of sysUpTime."

::= { ntpEntStatus 16 }

ntpEntStatPktModeTable OBJECT-TYPE

SYNTAX SEQUENCE OF NtpEntStatPktModeEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"The number of packets sent and received by packet mode.

One entry per packet mode."

::= { ntpEntStatus 17 }

ntpEntStatPktModeEntry OBJECT-TYPE

SYNTAX NtpEntStatPktModeEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A statistical record of the number of packets sent and received for each packet mode."

INDEX { ntpEntStatPktMode }
 ::= { ntpEntStatPktModeTable 1 }

NtpEntStatPktModeEntry ::= SEQUENCE {
 ntpEntStatPktMode INTEGER,
 ntpEntStatPktSent Counter32,
 ntpEntStatPktReceived Counter32
 }

ntpEntStatPktMode OBJECT-TYPE

SYNTAX INTEGER {
 symetricactive(1),
 symetricpassive(2),
 client(3),
 server(4),
 broadcastserver(5),
 broadcastclient(6)
 }

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"The NTP packet mode."

::= { ntpEntStatPktModeEntry 1 }

ntpEntStatPktSent OBJECT-TYPE

SYNTAX Counter32

UNITS "packets"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of NTP packets sent with this packet mode. Discontinuities in the value of this counter can occur upon cold start or reinitialization of the NTP entity, the management system and at other times as indicated by discontinuities in the value of sysUpTime."

::= { ntpEntStatPktModeEntry 2 }

ntpEntStatPktReceived OBJECT-TYPE

SYNTAX Counter32

UNITS "packets"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of NTP packets received with this packet mode."

Discountinuities in the value of this counter can occur upon cold start or reinitialization of the NTP entity, the management system and at other times as indicated by discontinuities in the value of sysUpTime."

```
::= { ntpEntStatPktModeEntry 3 }
```

```
--
```

```
-- Section 3: The status of all currently mobilized associations
```

```
--
```

```
ntpAssociationTable OBJECT-TYPE
```

```
SYNTAX          SEQUENCE OF NtpAssociationEntry
```

```
MAX-ACCESS      not-accessible
```

```
STATUS          current
```

```
DESCRIPTION
```

```
"The table of currently mobilized associations."
```

```
::= { ntpAssociation 1 }
```

```
ntpAssociationEntry OBJECT-TYPE
```

```
SYNTAX          NtpAssociationEntry
```

```
MAX-ACCESS      not-accessible
```

```
STATUS          current
```

```
DESCRIPTION
```

```
"The table entry of currently mobilized associations."
```

```
INDEX          { ntpAssocId }
```

```
::= { ntpAssociationTable 1 }
```

```
NtpAssociationEntry ::= SEQUENCE {
```

```
    ntpAssocId          Unsigned32,
```

```
    ntpAssocName        Utf8String,
```

```
    ntpAssocRefId       DisplayString,
```

```
    ntpAssocAddressType InetAddressType,
```

```
    ntpAssocAddress     InetAddress,
```

```
    ntpAssocOffset      DisplayString,
```

```
    ntpAssocStratum     NtpStratum,
```

```
    ntpAssocStatusJitter DisplayString,
```

```
    ntpAssocStatusDelay DisplayString,
```

```
    ntpAssocStatusDispersion DisplayString
```

```
}
```

```
ntpAssocId OBJECT-TYPE
```

```
SYNTAX          Unsigned32 ( 1..99999 )
```

```
MAX-ACCESS      not-accessible
```

```
STATUS          current
```

```
DESCRIPTION
```

```
"The association ID. This is an internal, unique ID."
```

```
::= { ntpAssociationEntry 1 }
```

```
ntpAssocName      OBJECT-TYPE
    SYNTAX          Utf8String
    MAX-ACCESS      read-only
    STATUS           current
    DESCRIPTION
        "The hostname or other descriptive name for the association."
    ::= { ntpAssociationEntry 2 }

ntpAssocRefId      OBJECT-TYPE
    SYNTAX          DisplayString
    MAX-ACCESS      read-only
    STATUS           current
    DESCRIPTION
        "The reftclock driver ID, if available."
        -- a reftclock driver ID like "127.127.1.0" for non
        -- uni/multi/broadcast associations
    ::= { ntpAssociationEntry 3 }

ntpAssocAddressType OBJECT-TYPE
    SYNTAX          InetAddressType { ipv4(1), ipv6(2), ipv4z(3), ipv6z(4) }
    MAX-ACCESS      read-only
    STATUS           current
    DESCRIPTION
        "The type of address of the association.  Can be either IPv4 or
        IPv6 (both with or without zone index) and contains the type of
        address for unicast, multicast, and broadcast associations."
    ::= { ntpAssociationEntry 4 }

ntpAssocAddress    OBJECT-TYPE
    SYNTAX          InetAddress (SIZE (4|8|16|20))
    MAX-ACCESS      read-only
    STATUS           current
    DESCRIPTION
        "The IP address (IPv4 or IPv6, with or without zone index) of
        the association.  The type and size depends on the
        ntpAssocAddressType object.  Represents the IP address of a
        uni/multi/broadcast association."
    ::= { ntpAssociationEntry 5 }

ntpAssocOffset     OBJECT-TYPE
    SYNTAX          DisplayString
    MAX-ACCESS      read-only
    STATUS           current
    DESCRIPTION
        "The time offset to the association as a string."
        -- including unit, e.g., "0.032 ms" or "1.232 s"
    ::= { ntpAssociationEntry 6 }
```

```
ntpAssocStratum OBJECT-TYPE
    SYNTAX      NtpStratum
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The association stratum value."
    ::= { ntpAssociationEntry 7 }

ntpAssocStatusJitter OBJECT-TYPE
    SYNTAX      DisplayString
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The jitter in milliseconds as a string."
    ::= { ntpAssociationEntry 8 }

ntpAssocStatusDelay OBJECT-TYPE
    SYNTAX      DisplayString
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The network delay in milliseconds as a string."
    ::= { ntpAssociationEntry 9 }

ntpAssocStatusDispersion OBJECT-TYPE
    SYNTAX      DisplayString
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The root dispersion of the association."
        -- e.g., "6.927"
    ::= { ntpAssociationEntry 10 }

ntpAssociationStatisticsTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF NtpAssociationStatisticsEntry
    MAX-ACCESS   not-accessible
    STATUS      current
    DESCRIPTION
        "The table of statistics for current associations."
    ::= { ntpAssociation 2 }

ntpAssociationStatisticsEntry OBJECT-TYPE
    SYNTAX      NtpAssociationStatisticsEntry
    MAX-ACCESS   not-accessible
    STATUS      current
    DESCRIPTION
        "The table entry of statistics for current associations."
    INDEX      { ntpAssocId }
```



```
::= { ntpAssociationStatisticsTable 1 }

NtpAssociationStatisticsEntry ::= SEQUENCE {
    ntpAssocStatInPkts      Counter32,
    ntpAssocStatOutPkts     Counter32,
    ntpAssocStatProtocolError Counter32
}

ntpAssocStatInPkts OBJECT-TYPE
    SYNTAX      Counter32
    UNITS       "packets"
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The total number of NTP messages delivered to the
        NTP entity from this association.
        Discontinuities in the value of this counter can occur
        upon cold start or reinitialization of the NTP entity, the
        management system and at other times as indicated by
        discontinuities in the value of sysUpTime."

::= { ntpAssociationStatisticsEntry 1 }

ntpAssocStatOutPkts OBJECT-TYPE
    SYNTAX      Counter32
    UNITS       "packets"
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The total number of NTP messages delivered to the
        transport service by this NTP entity for this
        association.
        Discontinuities in the value of this counter can occur
        upon cold start or reinitialization of the NTP entity, the
        management system and at other times as indicated by
        discontinuities in the value of sysUpTime."

::= { ntpAssociationStatisticsEntry 2 }

ntpAssocStatProtocolError OBJECT-TYPE
    SYNTAX      Counter32
    UNITS       "packets"
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The total number of NTP messages that were delivered
        to this NTP entity from this association and this entity
        was not able to process due to an NTP protocol error."
```

Discontinuities in the value of this counter can occur upon cold start or reinitialization of the NTP entity, the management system and at other times as indicated by discontinuities in the value of sysUpTime."

```
::= { ntpAssociationStatisticsEntry 3 }
```

```
--
-- Section 4: Control objects
--
```

ntpEntHeartbeatInterval OBJECT-TYPE

```
SYNTAX      Unsigned32
```

```
UNITS       "seconds"
```

```
MAX-ACCESS  read-write
```

```
STATUS      current
```

```
DESCRIPTION
```

"The interval at which the ntpEntNotifHeartbeat notification should be sent, in seconds. If set to 0 and the entNotifHeartbeat bit in ntpEntNotifBits is 1, then ntpEntNotifHeartbeat is sent once.

This value is stored persistently and will be restored to its last set value upon cold start or restart."

```
DEFVAL { 60 }
```

```
::= { ntpEntControl 1 }
```

ntpEntNotifBits OBJECT-TYPE

```
SYNTAX      BITS {
                notUsed(0), -- Used to sync up bit and notification
                           -- indices
                entNotifModeChange(1),
                entNotifStratumChange(2),
                entNotifSyspeerChanged(3),
                entNotifAddAssociation(4),
                entNotifRemoveAssociation(5),
                entNotifConfigChanged(6),
                entNotifLeapSecondAnnounced(7),
                entNotifHeartbeat(8)
            }
```

```
MAX-ACCESS  read-write
```

```
STATUS      current
```

```
DESCRIPTION
```

"A bit for each notification. A 1 for a particular bit enables that particular notification, a 0 disables it.

This value is stored persistently and will be restored to its last set value upon cold start or restart."

```
::= { ntpEntControl 2 }
```

```
--
-- Section 5: Notification objects
--

ntpEntNotifMessage OBJECT-TYPE
    SYNTAX      Utf8String
    MAX-ACCESS  accessible-for-notify
    STATUS      current
    DESCRIPTION
        "Used as a payload object for all notifications. Holds a
        cleartext event message."
    DEFVAL { "no event" }
    ::= { ntpEntNotifObjects 1 }

--
-- SNMP notification definitions
--

ntpEntNotifications OBJECT IDENTIFIER ::= { ntpSnmpMIB 0 }

ntpEntNotifModeChange NOTIFICATION-TYPE
    OBJECTS      { ntpEntStatusCurrentMode }
    STATUS      current
    DESCRIPTION
        "The notification to be sent when the NTP entity changes mode,
        including starting and stopping (if possible)."
    ::= { ntpEntNotifications 1 }

ntpEntNotifStratumChange NOTIFICATION-TYPE
    OBJECTS      { ntpEntStatusDateTime, ntpEntStatusStratum,
                  ntpEntNotifMessage }
    STATUS      current
    DESCRIPTION
        "The notification to be sent when stratum level of NTP changes."
    ::= { ntpEntNotifications 2 }

ntpEntNotifSyspeerChanged NOTIFICATION-TYPE
    OBJECTS      { ntpEntStatusDateTime, ntpEntStatusActiveRefSourceId,
                  ntpEntNotifMessage }
    STATUS      current
    DESCRIPTION
        "The notification to be sent when a (new) syspeer has been
        selected."
    ::= { ntpEntNotifications 3 }

ntpEntNotifAddAssociation NOTIFICATION-TYPE
    OBJECTS      { ntpEntStatusDateTime, ntpAssocName, ntpEntNotifMessage }
    STATUS      current
```

DESCRIPTION

"The notification to be sent when a new association is mobilized."

::= { ntpEntNotifications 4 }

ntpEntNotifRemoveAssociation NOTIFICATION-TYPE

OBJECTS { ntpEntStatusDateTime, ntpAssocName, ntpEntNotifMessage }

STATUS current

DESCRIPTION

"The notification to be sent when an association is demobilized."

::= { ntpEntNotifications 5 }

ntpEntNotifConfigChanged NOTIFICATION-TYPE

OBJECTS { ntpEntStatusDateTime, ntpEntNotifMessage }

STATUS current

DESCRIPTION

"The notification to be sent when the NTP configuration has changed, e.g., when the system connected to the Internet and was assigned a new IP address by the ISPs DHCP server."

::= { ntpEntNotifications 6 }

ntpEntNotifLeapSecondAnnounced NOTIFICATION-TYPE

OBJECTS { ntpEntStatusDateTime, ntpEntNotifMessage }

STATUS current

DESCRIPTION

"The notification to be sent when a leap second has been announced."

::= { ntpEntNotifications 7 }

ntpEntNotifHeartbeat NOTIFICATION-TYPE

OBJECTS { ntpEntStatusDateTime, ntpEntStatusCurrentMode,
ntpEntHeartbeatInterval, ntpEntNotifMessage }

STATUS current

DESCRIPTION

"The notification to be sent periodically (as defined by ntpEntHeartbeatInterval) to indicate that the NTP entity is still alive."

::= { ntpEntNotifications 8 }

--

-- Conformance/Compliance statements

--

ntpEntConformance OBJECT IDENTIFIER ::= { ntpSnmplib 2 }

ntpEntCompliances OBJECT IDENTIFIER ::= { ntpEntConformance 1 }

ntpEntGroups OBJECT IDENTIFIER ::= { ntpEntConformance 2 }

```
ntpEntNTPCompliance MODULE-COMPLIANCE
  STATUS      current
  DESCRIPTION
    "The compliance statement for SNMP entities that use NTP and
    implement the NTP MIB."
  MODULE -- this module
    MANDATORY-GROUPS {
        ntpEntObjectsGroup1
    }
    ::= { ntpEntCompliances 1 }

ntpEntSNTPCompliance MODULE-COMPLIANCE
  STATUS      current
  DESCRIPTION
    "The compliance statement for SNMP entities that use SNTP and
    implement the NTP MIB."
  MODULE -- this module
    MANDATORY-GROUPS {
        ntpEntObjectsGroup1
    }
    GROUP ntpEntObjectsGroup2
    DESCRIPTION
        "Optional object group."
    GROUP ntpEntNotifGroup
    DESCRIPTION
        "Optional notifications for this MIB."
    ::= { ntpEntCompliances 2 }

ntpEntObjectsGroup1 OBJECT-GROUP
  OBJECTS {
      ntpEntSoftwareName,
      ntpEntSoftwareVersion,
      ntpEntSoftwareVendor,
      ntpEntSystemType,
      ntpEntStatusEntityUptime,
      ntpEntStatusDateTime,
      ntpAssocName,
      ntpAssocRefId,
      ntpAssocAddressType,
      ntpAssocAddress
  }
  STATUS      current
  DESCRIPTION
    "A collection of objects for the NTP MIB."
  ::= { ntpEntGroups 1 }

ntpEntObjectsGroup2 OBJECT-GROUP
  OBJECTS {
```

```
    ntpEntTimeResolution,
    ntpEntTimePrecision,
    ntpEntTimeDistance,
    ntpEntStatusCurrentMode,
    ntpEntStatusStratum,
    ntpEntStatusActiveRefSourceId,
    ntpEntStatusActiveRefSourceName,
    ntpEntStatusActiveOffset,
    ntpEntStatusNumberOfRefSources,
    ntpEntStatusDispersion,
    ntpEntStatusLeapSecond,
    ntpEntStatusLeapSecDirection,
    ntpEntStatusInPkts,
    ntpEntStatusOutPkts,
    ntpEntStatusBadVersion,
    ntpEntStatusProtocolError,
    ntpEntStatusNotifications,
    ntpEntStatPktSent,
    ntpEntStatPktReceived,
    ntpAssocOffset,
    ntpAssocStratum,
    ntpAssocStatusJitter,
    ntpAssocStatusDelay,
    ntpAssocStatusDispersion,
    ntpAssocStatInPkts,
    ntpAssocStatOutPkts,
    ntpAssocStatProtocolError,
    ntpEntHeartbeatInterval,
    ntpEntNotifBits,
    ntpEntNotifMessage
}
STATUS          current
DESCRIPTION
    "A collection of objects for the NTP MIB."
 ::= { ntpEntGroups 2 }

ntpEntNotifGroup NOTIFICATION-GROUP
    NOTIFICATIONS {
        ntpEntNotifModeChange,
        ntpEntNotifStratumChange,
        ntpEntNotifSyspeerChanged,
        ntpEntNotifAddAssociation,
        ntpEntNotifRemoveAssociation,
        ntpEntNotifConfigChanged,
        ntpEntNotifLeapSecondAnnounced,
        ntpEntNotifHeartbeat
    }
STATUS          current
```

DESCRIPTION

"A collection of notifications for the NTP MIB"
 ::= { ntpEntGroups 3 }

END

6. IANA Considerations

The MIB module in this document uses the following IANA-assigned OBJECT IDENTIFIER values recorded in the SMI Numbers registry:

Descriptor -----	OBJECT IDENTIFIER value -----
ntpSnmp	{ mib-2 197 }

7. Security Considerations

There are currently two management objects defined in this MIB module with a MAX-ACCESS clause of read-write and/or read-create. Such objects may be considered sensitive or vulnerable in some network environments. The support for SET operations in a non-secure environment without proper protection can have a negative effect on network operations. These are the objects and their sensitivity/vulnerability:

ntpEntHeartbeatInterval controls the interval of heartbeat notifications. If set to 1, this will cause the NTP entity to send one notification each second. This is the maximum rate (1/s) that can be generated automatically. If it is set to 0, then one single heartbeat notification will be created and no further automatically generated notification is sent. This functionality can be used to create notifications at a higher rate (as high as the object can be written).

ntpEntNotifBits enables/disables notifications. Could be used to switch off notifications in order to delay or eliminate the notification for critical and important events.

Some of the readable objects in this MIB module (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP. These are the tables and objects and their sensitivity/vulnerability:

ntpEntSoftwareName, ntpEntSoftwareVersion, ntpEntSoftwareVendor, and ntpEntSystemType all can be used to identify software and its version as well as the operating system and hardware platform. This might help a potential attacker to find security problems and therefore can be used in the preparation of an attack.

SNMP versions prior to SNMPv3 did not include adequate security. Even if the network itself is secure (for example by using IPsec), even then, there is no control as to who on the secure network is allowed to access and GET/SET (read/change/create/delete) the objects in this MIB module. It is RECOMMENDED that implementers consider the security features as provided by the SNMPv3 framework (see RFC 3410 [RFC3410], section 8), including full support for the SNMPv3 cryptographic mechanisms (for authentication and privacy). Further, deployment of SNMP versions prior to SNMPv3 is NOT RECOMMENDED. Instead, it is RECOMMENDED to deploy SNMPv3 and to enable cryptographic security. It is then a customer/operator responsibility to ensure that the SNMP entity giving access to an instance of this MIB module is properly configured to give access to the objects only to those principals (users) that have legitimate rights to indeed GET or SET (change/create/delete) them.

8. Acknowledgments

Bert Wijnen provided valuable feedback as the MIB Doctor for this document.

9. References

9.1. Normative References

- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", BCP 14, RFC 2119, March 1997.
- [RFC5905] Mills, D., Martin, J., Ed., Burbank, J., and W. Kasch, "Network Time Protocol Version 4: Protocol and Algorithms Specification", RFC 5905, June 2010.
- [RFC2287] Krupczak, C. and J. Saperia, "Definitions of System-Level Managed Objects for Applications", RFC 2287, February 1998.
- [RFC2578] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Structure of Management Information Version 2 (SMIv2)", STD 58, RFC 2578, April 1999.

- [RFC2579] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Textual Conventions for SMIV2", STD 58, RFC 2579, April 1999.
- [RFC2580] McCloghrie, K., Perkins, D., and J. Schoenwaelder, "Conformance Statements for SMIV2", STD 58, RFC 2580, April 1999.
- [RFC4001] Daniele, M., Haberman, B., Routhier, S., and J. Schoenwaelder, "Textual Conventions for Internet Network Addresses", RFC 4001, February 2005.

9.2. Informative References

- [RFC3410] Case, J., Mundy, R., Partain, D., and B. Stewart, "Introduction and Applicability Statements for Internet-Standard Management Framework", RFC 3410, December 2002.

Authors' Addresses

Heiko Gerstung
Meinberg Funkuhren Gmbh & Co. KG
Lange Wand 9
Bad Pyrmont 31812
Germany

Phone: +49 5281 9309 25
EMail: heiko.gerstung@meinberg.de

Chris Elliott
1516 Kent St.
Durham, NC 27707
USA

Phone: +1-919-308-1216
EMail: chelliott@pobox.com

Brian Haberman (editor)
Johns Hopkins University Applied Physics Lab
11100 Johns Hopkins Road
Laurel, MD 20723-6099
US

Phone: +1 443 778 1319
EMail: brian@innovationslab.net

